


### **AUTOMATIC UPDATE: ONLINE MODE (For example: WINDOWS 7 -32 Bits):**


Once the TRS5000 PC software has been installed, the programme will launch, either automatically from the installer itself (Launch TRS5000) or from the TRS5000 EVO icon that the software places on the desktop.

If you have a Windows 7 (32 / 64 bits) operating system, when you connect the TRS EVO to the PC with a USB cable, it will detect that new hardware has been connected and will start to allocate a virtual port as well as automatically loading the driver.

You cannot communicate with the EVO until this process has finished.



Once the operating system has allocated a virtual port, which is different for each user, connect to the TRS EVO by selecting that port and clicking (Start Communication).




The connection is identical to the previous TRS5000 version, as it basically uses the same graphic interface.

In the drop down OPTIONS menu select SETTINGS and find the virtual USB port allocated by the operating system, in this case COM10.

If it fails to appear automatically, you can select it in the tab with the arrow from the Communications Port drop-down menu, where you can see all the ports currently open on the PC.

Click RELOAD COM PORT LIST to refresh the ports currently open on the PC.



***If you have only one TRS5000 EVO, which is always physically connected to the same USB port, we recommend keeping the “Enable communication on program start” option selected. This function enables you to establish the EVO-PC communications as soon as the TRS 5000 EVO software has been executed, without having to go to the Options / Settings menu, select the port and establish the connection. The USB cable must always be connected to the same USB port and the TRS EVO must be switched on before launching the PC software.***

Once communication has been established, the COM LED on the bottom left will turn from red to green.



**Until communication has been established between the PC and the TRS5000 EVO, (COM LED in GREEN), some of the software functions remain disabled, such as:**

- **Online update (automatic function).**
- **All the functions of the Key menu.**
- **Send text / Update programme (manual function).**

**Once communication has been established, all functions except **Web Update** are enabled. This function only works if the machine connected is a TRS5000 EVO.**

Automatic online update is only available for TRS5000 EVO machines.

The programme automatically detects whether the machine is connected and enables or disables this function.



**In order to execute both update processes (Manual or Automatic,) the client must have registered using JMA website.**


On clicking ONLINE UPDATE, the following menu appears:



Sections (1), (2) and (3) respectively display the TRS EVO's manufacturer serial number, its current firmware version and the version of the PC software installed on the computer.

To start the update process, the customer must contact our JMA server and launch the request by clicking Check for Update button (4).

On clicking Check for Update, (4), the programme will check whether the customer is registered. If customer is not registered, the following message will be displayed:



When you click YES (Register using the JMA website now), the program access to JMA web server and registration form will appear.



***Registration requirements:***  
***MANDATORY: AN INTERNET CONNECTION.***

LOGIN

### REGISTRATION FORM

Please, fill in the form with all the required informations to register You on the JMA update website.


|                                       |   |
|---------------------------------------|---|
| COMPANY *                             | JMA   |
| CONTACT *                             | Jonkar  |
| ADDRESS *                             | C/ BIDEKURTZETA 6, 20500, MONDRAGON, SPAIN  |
| CITY *                                | MONDRA  |
| POSTAL CODE *                         | 20500   |
| COUNTRY *                             | Spain   |
| PHONE *                               | 943793000   |
| FAX                                   |   |
| EMAIL *                               | jk.olabarria@jma.es (it will be Your username)  |
| CONFIRM EMAIL *                       | jk.olabarria@jma.es   |
| WEBSITE                               |   |
| PASSWORD *                            | jma222jma (min 8 - max 20)  |
| PASSWORD CONFIRM *                    | jma222jma (min 8 - max 20)  |
| NEWSLETTER                            | <input checked="" type="checkbox"/>   |
| PRIVACY *                             | All the elements making up the content of this web site, identified by the dominion name jma.es, including the trade names, trademarks and logos that appear on the web site, are protected by Copyright Law. The copyright on the content and graphic design of this web site is the exclusive property of Alejandro Altuna S.A It is expressly prohibited to resend, transmit, modify, reproduce, distribute, market or transform it without the express authorisation in writing of Alejandro Altuna S.A. Therefore, except for expressly authorised personal or private use, the total or partial resending, transmission, modification, reproduction, distribution, marketing and/or transformation of the content of this web site shall constitute an infringement of the copyright of Alejandro Altuna S.A. Any user infringing the copyright shall be held liable. Alejandro Altuna S.A. reserve the right to deny access, at any time at their discretion and without prior notice, to any user to this web site or <input checked="" type="checkbox"/> |
| SERIAL NUMBER *                       | 1ES0100000000001  |
| PC SOFT RELEASE *                     | 3 . 21 eg. 2.00   |
| FIRMWARE RELEASE *                    | 1 . 08 eg. 1.23   |
| <input type="button" value="SUBMIT"/> |   |

registration.asp

© Alejandro Altuna. Todos los derechos reservados.

Once you select SUBMIT, and once the process has been satisfactorily completed, a new menu inform us that the client has been correctly registered in the JMA database.

The 2 types of update and how to proceed in each case are also detailed.



The registration confirmation menu also specifies that the client will receive an e-mail with their (User name) and (Password) allowing them to access the client website and the update files in case they wish to manually update the TRS EVO.

The standard mail is:

***Congratulations, you have registered your TRS successfully.***

***Your user name and password that you will need to access the JMA website are:***

***User name: [jk.olabarria@jma.es](mailto:jk.olabarria@jma.es)***

***Password: jma111jma***

***Click [here](#) to enter the client's web page. This link takes the client to the OFFLINE update mode.***

***Thank you for your attention.***


***Best regards,***

***JMA Technical Assistance***


As you are in the automatic update process, close the registration confirmation WEB page and go back to the PC software.

The steps to follow to update the TRS5000 EVO firmware are described below:


1. Once you have clicked Check for Update (4), the programme checks whether there are more recent firmware and PC Software files available on the JMA server.




2. In this case, an emerging menu indicates that there is only one superior firmware version (1.09). Download it by clicking YES.




- The programme downloads the files to update from the JMA server to customer's PC. Once the files have been successfully downloaded, the (Update TRS) button is automatically enabled. Click on it to launch the update.




- The programme updates the firmware file first. On successful completion, click (Exit) to enable Micro restart and to proceed to update the second part of the firmware updating process, which is Text file sending, in the language preferred by customer.



- Once customer have selected preferred language and click on (Upload), a downloading progress status bar will show us how near we are to complete TXT file sending. Clicking now (Exit) button we will finish the whole firmware updating process.




To check whether the process was successful, click (Check for Updates) again and the following emerging message should appear:



Showing that the firmware version has been updated from 1.08 to 1.09 and the TRS update button has been automatically disabled.


If you find more up to date versions of both, firmware and PC Software available when you click (Check for Updates), they will then be updated.



Firstly, you could download (Set-Up) for installing the PC Software from JMA Server, which will automatically be saved in a particular directory on the PC.




As soon as the download finishes, the (Update PC Soft) button is enabled and as there is also a firmware update pending, a message indicating the availability of a firmware update will also appear.



It's better to update the TRS EVO firmware first as it will take less time than updating the PC Software. Click YES and then repeat steps 1-5 as described above.

As for the software update, when you click Update PC Software, the following emerging menu appears:



Here, after clicking OK, the PC Software is closed and the installation described in Word document FAST\_SETUP\_EVO\_Revxx.docx, section A, steps 1 - 5 begins.

If the client wishes to access the directory where all of the information downloaded from the JMA server is saved after executing the Update TRS and Update PC Soft commands, they simply need to click on Open Update Files Folder.

